Distributed by:

JAMECO® ELECTRONICS

www.Jameco.com ✦ 1-800-831-4242

The content and copyrights of the attached material are the property of its owner.

Jameco Part Number 230412

	Tool w/ Die Set	Die Set Only	Connector Type(s)	Cable Type(s)	Crimp Sizes/Type	Connector Manufacturers or Remarks
	1317	2034	BNC/TNC, 3 Piece	RG58, RG59, RG62AU	0.256"/0.213"/0.068" HEX	Common 2-piece and 3-piece BNC/TNC
	1319	2039	N-type, MS39012 Type	RG8, RG11, RG213, RG216	0.415"/0.095" HEX	Crimps Pins and Ferrules
	1328	2042	CATV "F" Type	RG59, RG6 Video Cable	0.346"/0.315"/0.256" HEX	CATV "F" 1- and 2-piece
	1335	2046	Thinnet, BNC/TNC, Mini-UHF 50 and 75 ohm	RG58, RG174, AT&T 735	0.213"/0.178"/0.068" HEX and 0.042"SQ	50/75 ohm small 2-piece and 3-piece BNC/TNC (Kings, ADC, etc.)
	1336	2047	BNC/TNC, and Mini-UHF 50 and 75 ohm	RG59, RG62, Belden 8281	0.315"/0.252"/0.068" HEX and 0.042"SQ	75 ohm 2-piece and 3-piece BNC/TNC (Kings, ADC, Amphenol, etc.)
	1337	2050	BNC/TNC	RG8, RG213	0.402"/0.094"/0.079" HEX	Common 2-piece and 3-piece BNC/TNC
	1338	2051	BNC/TNC	RG174, RG179, and Small Cable Conn.	0.178"/0.128"/0.068" HEX	Common 2-piece and 3-piece BNC/TNC/SMA/SMB
	1347	2075	BNC/TNC	RG58, RG59, RG62AU, RG6 Teflon/Plenum	0.325"/0.215"/0.065" HEX	2-piece and 3-piece BNC/TNC (AIM/Cambridge, GEM)
	1348	2076	BNC/TNC	RG6, RG58	0.320"/0.210"/0.185" HEX	2-piece BNC/TNC (AIM/ Cambridge, Kings, Amphenol, GEM)
	1349	2082	BNC/TNC	Belden 1694A, Belden 1695A	0.315"/0.068" HEX	Common 2-piece and 3-piece BNC/TNC
	1356	2045	BNC and CATV "F" Type & HDTV	RG6 and RG6 Quad, Belden 1694A	0.360"/0.324"/0.068" HEX	Common 2-piece and 3-piece BNC/TNC, and CATV "F" 2-piece
	1363 New	2653	SMA, SMB, Mini-59 BNC/TNC, Mini-UHF	RG58, Mini-59, RG-174, small coaxial	0.128"/0.213"/0.197" /0.178"/0.068" HEX and 0.042"SQ	Common 2-piece and 3-piece SMA/SMB/BNC/TNC & mini-UHF
	1365 New	2656	N-type Plugs	RG8 , RG11, RG213	0.429"/0.100"/0.080" HEX	Common 2-piece and 3-piece "N"-Type (Kings, ADC, Amphenol, etc.)
	1366 New	2648	HDTV SMA, True 75 ohm BNC/TNC, Mini-UHF, 75 ohm	RG174, RG59/62, mini-coaxial	0.255"/0.197" /0.178"/0.068" HEX and 0.042"SQ	Common 2-piece and 3-piece BNC/TNC (Kings, ADC, Amphenol, etc.)
	1367 New	2649	HDTV BNC/TNC/ CATV "F" True 75 ohm	RG59, RG6, BELDEN 8281, BELDEN 1694A	0.324"/0.255"/0.068" HEX and 0.052"/0.042"SQ	Common 2-piece and 3-piece BNC/TNC (Kings, ADC, Amphenol, etc.)
	1368 New	2657	HDTV BNC/TNC True 75 ohm	RG6, BELDEN 1694, BELDEN 1694A	0.278"/0.275"/0.068" HEX and 0.042"SQ	Common 3-piece BNC/TNC (Kings & ADC HDTV)